

Fourier Transform Table

$x(t)$	$X(f)$	$X(\omega)$
$\delta(t)$	1	1
1	$\delta(f)$	$2\pi\delta(\omega)$
$\delta(t - t_0)$	$e^{-j2\pi f t_0}$	$e^{-j\omega t_0}$
$e^{j2\pi f_0 t}$	$\delta(f - f_0)$	$2\pi\delta(\omega - \omega_0)$
$\cos(2\pi f_0 t)$	$\frac{1}{2} [\delta(f - f_0) + \delta(f + f_0)]$	$\pi [\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$
$\sin(2\pi f_0 t)$	$\frac{1}{2j} [\delta(f - f_0) - \delta(f + f_0)]$	$-j\pi [\delta(\omega - \omega_0) - \delta(\omega + \omega_0)]$
$\text{rect}(t)$	$\text{sinc}(f)$	$\text{sinc}\left(\frac{\omega}{2\pi}\right)$
$\text{sinc}(t)$	$\text{rect}(f)$	$\text{rect}\left(\frac{\omega}{2\pi}\right)$
$\Lambda(t)$	$\text{sinc}^2(f)$	$\text{sinc}^2\left(\frac{\omega}{2\pi}\right)$
$\text{sinc}^2(t)$	$\Lambda(f)$	$\Lambda\left(\frac{\omega}{2\pi}\right)$
$e^{-\alpha t} u(t), \quad \alpha > 0$	$\frac{1}{\alpha + j2\pi f}$	$\frac{1}{\alpha + j\omega}$
$t e^{-\alpha t} u(t), \quad \alpha > 0$	$\frac{1}{(\alpha + j2\pi f)^2}$	$\frac{1}{(\alpha + j\omega)^2}$
$e^{-\alpha t }, \quad \alpha > 0$	$\frac{2\alpha}{(\alpha^2 + (2\pi f)^2)}$	$\frac{2\alpha}{(\alpha^2 + (\omega)^2)}$
$e^{-\pi t^2}$	$e^{-\alpha f^2}$	$e^{-\alpha f^2}$
$\text{sgn}(t)$	$\frac{1}{j\pi f}$	$\frac{2}{j\omega}$
$u(t)$	$\frac{1}{2} \delta(f) + \frac{1}{j2\pi f}$	$\pi\delta(\omega) + \frac{1}{j\omega}$
$\frac{d}{dt} \delta(t)$	$j2\pi f$	$j\omega$
$\sum_{n=-\infty}^{\infty} \delta(t - nT_0)$	$\frac{1}{T_0} \sum_{n=-\infty}^{\infty} \delta\left(f - \frac{n}{T_0}\right)$	$\frac{1}{T_0} \sum_{n=-\infty}^{\infty} \delta\left(\omega - \frac{2\pi n}{T_0}\right)$